## DATOS PARA ARRANQUE CON DEVANADOS PARCIALES 220 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO	BREAKER	FUSIBLES	2 Contactores	2 Contactores	RELE TER.	RELE TER.
HP	KW	(A)	(A)	(A)	G.E.	C. S. C.	G.E.	C. SC.
3	2,2	9,6	16	32	CL00 (9 A)	C1-D09	RT1L(4-6,3)	R2-D1310 (4-6)
5	3,7	15,2	25	32	CL00 (9 A)	C1-D12	RT1M( 5,5 - 8,5 )	R2-D1312 ( 5,5 - 8 )
7,5	5,5	21	40	50	CL01 (12 A)	C1-D18	RT1H(8-12)	R2-D1316 (9 - 13)
10	7,5	28	50	63	CL02 (18 A)	C1-D25	RT1P( 10 - 16 )	R2-D1321 ( 12 - 18 )
15	11	42	75	125	CL25 ( 25 A )	C1-D32	RT1T( 17,5 - 22 )	R2-D1322 ( 17 - 25 )
20	15	54	100	125	CL04 (32 A)	C1-D40	RT1V( 25 - 32 )	R2-D3353 ( 23 -32 )GDE
25	18,5	68	125	125	CL45 (40 A)	C1-D50	RT1W(30 - 40)	R2-D3355 ( 30 - 40 )
30	22	80	150	200	CL06 (50 A)	C1-D65	RT2E(30 - 43)	R2-D3357 ( 37 - 50 )
40	30	104	175	200	CL07 (65 A)	C1-D80	RT2G( 45 - 55 )	R2-D3359 ( 48 - 65 )
50	37	130	200	250	CL08 (80 A)	C1-D95	RT2J( 64 - 82 )	R2-D3361 (55 - 70)
60	45	154	250	315	CL08 (80 A)	C1-F115	RT2J(64 - 82)	R2-D3363 ( 63 - 80 )
75	55	182	300	350	CL09 (95 A)	C1-F150	RT2L(78 - 97)	R2-D3365 ( 80 - 93 )
100	75	248	400	400	CK75 ( 150 A )	C1-F185	RT3E( 110 - 140 )	LR1-F160 (100-160 )*

## DATOS PARA ARRANQUE CON DEVANADOS PARCIALES 440 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO	BREAKER	FUSIBLES	2 Contactores	2 Contactores	RELE TER.	RELE TER.
HP	KW	(A)	(A)	(A)	G.E.	C. S. C.	G.E.	C. SC.
3	2,2	4,8	10	16	CL00 (9 A)	C1-D09	RT1J( 1,8 - 2,7 )	R2-D1307 ( 1,6 - 2,5 )
5	3,7	7,6	16	16	CL00 (9 A)	C1-D09	RT1K(2,5-4)	R2-D1308 ( 2,5 - 4 )
7,5	5,5	11	20	25	CL00 (9 A)	C1-D09	RT1L(4-6,3)	R2-D1310 (4-6)
10	7,5	14	25	32	CL00 (9 A)	C1-D12	RT1M(5,5 - 8,5)	R2-D1312 ( 5,5 - 8 )
15	11	21	40	50	CL01 (12 A)	C1-D18	RT1N(8-12)	R2-D1316 (9 - 13)
20	15	27	50	63	CL02 (18 A)	C1-D25	RT1P( 10 - 16 )	R2-D1321 ( 12 -18 )
25	18,5	34	63	80	CL02 (18 A)	C1-D25	RT1S( 14,5 - 17,5 )	R2-D1321 ( 12 -18 )
30	22	40	75	100	CL25 ( 25 A )	C1-D32	RT1T( 17,5 - 22 )	R2-D1322 ( 17 - 25 )
40	30	52	100	125	CL04 (32 A)	C1-D40	RT1V( 25 - 32 )	R2-D3353 ( 23-32)GDE.
50	37	65	125	125	CL45 (40 A)	C1-D50	RT1W(30 - 40)	R2-D3355 ( 30 - 40 )
60	45	77	125	160	CL45 (40 A)	C1-D65	RT1W(30 - 40)	R2-D3355 ( 30 - 40 )
75	55	96	150	160	CL06 (50 A)	C1-D80	RT2G( 42 - 55 )	R2-D3357 ( 37 - 50 )
100	75	124	200	250	CL07 (65 A)	C1-D95	RT2H( 54 - 65 )	R2-D3359 ( 48 - 65 )