

DATOS PARA ARRANQUE CON DEVANADOS PARCIALES 220 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO		BREAKER	FUSIBLES	2 Contactores	2 Contactores	RELE TER.	RELE TER.
HP	KW	(A)	(A)	(A)		G.E.	C. S. C.	G.E.	C. S. .C.
3	2,2	9,6	16	32		CL00 (9 A)	C1-D09	RT1L(4 - 6,3)	R2-D1310 (4 - 6)
5	3,7	15,2	25	32		CL00 (9 A)	C1-D12	RT1M(5,5 - 8,5)	R2-D1312 (5,5 - 8)
7,5	5,5	21	40	50		CL01 (12 A)	C1-D18	RT1H(8 - 12)	R2-D1316 (9 - 13)
10	7,5	28	50	63		CL02 (18 A)	C1-D25	RT1P(10 - 16)	R2-D1321 (12 - 18)
15	11	42	75	125		CL25 (25 A)	C1-D32	RT1T(17,5 - 22)	R2-D1322 (17 - 25)
20	15	54	100	125		CL04 (32 A)	C1-D40	RT1V(25 - 32)	R2-D3353 (23 -32)GDE
25	18,5	68	125	125		CL45 (40 A)	C1-D50	RT1W(30 - 40)	R2-D3355 (30 - 40)
30	22	80	150	200		CL06 (50 A)	C1-D65	RT2E(30 - 43)	R2-D3357 (37 - 50)
40	30	104	175	200		CL07 (65 A)	C1-D80	RT2G(45 - 55)	R2-D3359 (48 - 65)
50	37	130	200	250		CL08 (80 A)	C1-D95	RT2J(64 - 82)	R2-D3361 (55 - 70)
60	45	154	250	315		CL08 (80 A)	C1-F115	RT2J(64 - 82)	R2-D3363 (63 - 80)
75	55	182	300	350		CL09 (95 A)	C1-F150	RT2L(78 - 97)	R2-D3365 (80 - 93)
100	75	248	400	400		CK75 (150 A)	C1-F185	RT3E(110 - 140)	LR1-F160 (100-160)*

DATOS PARA ARRANQUE CON DEVANADOS PARCIALES 440 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO		BREAKER	FUSIBLES	2 Contactores	2 Contactores	RELE TER.	RELE TER.
HP	KW	(A)	(A)	(A)		G.E.	C. S. C.	G.E.	C. S. .C.
3	2,2	4,8	10	16		CL00 (9 A)	C1-D09	RT1J(1,8 - 2,7)	R2-D1307 (1,8 - 2,5)
5	3,7	7,6	16	16		CL00 (9 A)	C1-D09	RT1K(2,5 - 4)	R2-D1308 (2,5 - 4)
7,5	5,5	11	20	25		CL00 (9 A)	C1-D09	RT1L(4 - 6,3)	R2-D1310 (4 - 6)
10	7,5	14	25	32		CL00 (9 A)	C1-D12	RT1M(5,5 - 8,5)	R2-D1312 (5,5 - 8)
15	11	21	40	50		CL01 (12 A)	C1-D18	RT1N(8 - 12)	R2-D1316 (9 - 13)
20	15	27	50	63		CL02 (18 A)	C1-D25	RT1P(10 - 16)	R2-D1321 (12 - 18)
25	18,5	34	63	80		CL02 (18 A)	C1-D25	RT1S(14,5 - 17,5)	R2-D1321 (12 - 18)
30	22	40	75	100		CL25 (25 A)	C1-D32	RT1T(17,5 - 22)	R2-D1322 (17 - 25)
40	30	52	100	125		CL04 (32 A)	C1-D40	RT1V(25 - 32)	R2-D3353 (23-32)GDE.
50	37	65	125	125		CL45 (40 A)	C1-D50	RT1W(30 - 40)	R2-D3355 (30 - 40)
60	45	77	125	160		CL45 (40 A)	C1-D65	RT1W(30 - 40)	R2-D3355 (30 - 40)
75	55	96	150	160		CL06 (50 A)	C1-D80	RT2G(42 - 55)	R2-D3357 (37 - 50)
100	75	124	200	250		CL07 (65 A)	C1-D95	RT2H(54 - 65)	R2-D3359 (48 - 65)

