

CONSUMO DE LAS BOBINAS EN LOS CONTACTORES GE

CONTACTOR G.E.	CONSUMO MAXIMO DE BOBINA (V.A)		TRANSFORMADOR REQUERIDO
	ARRANQUE	SOSTENIMIENTO	V.A
CL00	35	5	40
CL01	35	5	40
CL02	35	5	40
CL25	35	5	40
CL03	105	11	63
CL04	105	11	63
CL45	105	11	63
CL06	215	15	100
CL07	215	15	100
CL08	215	15	100
CL09	215	15	100
CL10	215	15	100
CK75	400	32	250
CK08	400	32	250
CK85	830	60	400
CK09	830	60	400
CK95	340	13	160

CONSUMO DE LAS BOBINAS EN LOS CONTACTORES CSC

CONTACTOR CAMSCO	CONSUMO MAXIMO DE BOBINA (V.A)		TRANSFORMADOR REQUERIDO
	ARRANQUE	SOSTENIMIENTO	V.A
C1-D09	70	14	40
C1-D12	70	12	40
C1-D18	90	14	63
C1-D25	215	26	100
C1-D32	215	26	100
C1-D40	280	14	160
C1-D50	280	31	160
C1-D65	280	31	160
C1-D80	580	40	250
C1-D95	580	40	250
C1-F115	1205	73	400
C1-F150	1205	73	400
C1-F185	1205	73	400
C1-F225	1350	75	630
C1-F265	1350	75	630
C1-F330	1630	75	630
C1-F400	1630	75	630
C1-F500	1630	75	630

