



DATOS PARA ARRANQUES ESTRELLA TRIANGULO 220 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO			CONTACTORES G.E.	CONTACTORES C. S. C.	RELE TER.		RELE TER.	
HP	KW	(A)	(A)	(A)			RED Y DELTA	Y		G.E.
3	2,2	9,6	16	20	CL00/CB4(9A)	CL00/CB4	C1-D09	C1-D09	RT1L/CBR1 6.0(4-6,3)	R2-D1310(4-6)
5	3,7	15	25	32	CL01/CB5(12A)	CL00/CB4	C1-D18	C1-D09	RT1N/CBR1 13.0(8-12)	R2-D1314(7-10)
7,5	5,5	21	30	50	CL01/CB5(12A)	CL00/CB4	C1-D18	C1-D12	RT1P/CBR1 18.0(10-16)	R2-D1316(9-13)
10	7,5	28	40	63	CL02/CB7(18A)	CL00/CB4	C1-D32	C1-D18	RT1S/CBR1 18.0(14,5-17,5)	R2-D1321(12-18)
15	11	42	63	80	CL25/CB11(25A)	CL02/CB7	C1-D40	C1-D25	RT1U/CBR1 25.0(21-26)	R2-D3353(23-32)G
20	15	54	75	100	CL04/CB15(32A)	CL02/CB7	C1-D50	C1-D32	RT1W/CBR3 40.0(30-40)	R2-D3355(30-40)
25	18,5	68	100	125	CL45/CB18(40A)	CL25/CB11	C1-D65	C1-D40	RT1W/CBR3 40.0(30-40)	R2-D3355(30-40)
30	22	80	125	125	CL06/CB22(50A)	CL04/CB15	C1-D80	C1-D40	RT2G/CBR3 50.0(45-55)	R2-D3357(37-50)
40	30	104	150	200	CL07/CB30(65A)	CL45/CB18	C1-D95	C1-D50	RT2H/CBR3 65.0(54-65)	R2-D3359(48-65)
50	37	130	200	250	CL08/CB37(80A)	CL06/CB22	C1-F115	C1-D65	RT2J/CBR3 80.0(64-82)	R2-D3363(63-80)
60	45	154	225	250	CL09/CB45(95A)	CL07/CB30	C1-F150	C1-D80	RT2L(78-97)	R2-D3365(80-93.)
75	55	182	250	315	CL10/CB45(105A)	CL07/CB30	C1-F185	C1-D95	RT2M(90-110)	LR1-F125(95-125)
100	75	248	350	400	CK75(150A)	CL09	C1-F225	C1-F150	RT3F(140-190)	LR1-F160(100-160)

DATOS PARA ARRANQUES ESTRELLA TRIANGULO 440 VOLTIOS TRIFASICOS

POTENCIA		CONSUMO			CONTACTORES G.E.	CONTACTORES C. S. C.	RELETER.		RELETER.	
HP	KW	(A)	(A)	(A)			RED Y DELTA	Y		G.E.
3	2,2	4,8	10	16	CL00/CB4(9A)	CL00/CB4	C1-D09	C1-D09	RT1K/CBR1 4.0(2,5-4)	R2-D1308(2,5-4)
5	3,7	7,6	10	16	CL00/CB4(9A)	CL00/CB4	C1-D09	C1-D09	RT1L/CBR1 6.0(4-6,3)	R2-D1310(4-6)
7,5	5,5	11	16	16	CL00/CB4(9A)	CL00/CB4	C1-D12	C1-D09	RT1M/CBR1 8.0(5,5-8,5)	R2-D1312(5,5-8)
10	7,5	14	20	32	CL00/CB4(9A)	CL00/CB4	C1-D12	C1-D09	RT1M/CBR1 8.0(5,5-8,5)	R2-D1314(7-10)
15	11	21	32	50	CL01/CB5(12A)	CL00/CB4	C1-D18	C1-D12	RT1P/CBR1 18.0(10-16)	R2-D1316(9-13)
20	15	27	40	63	CL02/CB7(18A)	CL00/CB4	C1-D25	C1-D18	RT1P/CBR1 18.0(10-16)	R2-D1321(12-18)
25	18,5	34	50	80	CL25/CB11(25A)	CL01/CB5	C1-D32	C1-D18	RT1T/CBR1 25.0(17,5-22)	R2-D1322(17-25)
30	22	40	63	80	CL25/CB11(25A)	CL02/CB7	C1-D40	C1-D25	RT1U/CBR1 25.0(21-26)	R2-D1322(17-25)
40	30	52	75	100	CL04/CB15(32A)	CL02/CB7	C1-D50	C1-D25	RT1V/CBR2 32.0(25-32)	R2-D3353(23-32)G
50	37	65	100	125	CL45/CB18(40A)	CL25/CB11	C1-D65	C1-D32	RT1W/CBR3 40.0(30-40)	R2-D3355(30-40)
60	45	77	125	125	CL06/CB22(50A)	CL25/CB11	C1-D80	C1-D40	RT2G/CBR3 50.0(45-55)	R2-D3357(37-50)
75	55	96	150	160	CL07/CB30(65A)	CL04/CB15	C1-D95	C1-D50	RT2H/CBR3 65.0(54-65)	R2-D3359(48-65)
100	75	124	200	250	CL08/CB37(80A)	CL06/CB22	C1-F1115	C1-D65	RT2J/CBR3 80.0(64-82)	R2-D3363(63-80)

